

160 METERS — 1.8-2.0 MHz

| G | A | E | 2.000 | |
|---|-------------|--------------------------|-------------|---------------------------|
| █ | █ | █ | 1.999-2.000 | Beacons |
| | | | 1.995-2.000 | Experimental |
| | | | 1.910 | QRP SSB Calling Frequency |
| | | | 1.855 | W1AW Voice |
| | | | 1.843-2.000 | SSB, SSTV and Wideband |
| | | | 1.840-1.850 | SSB DX Window |
| | | | 1.838 | PSK31 |
| | | | 1.830-1.840 | CW DX |
| | | | 1.8175 | W1AW Code |
| | | | 1.810-1.830 | CW |
| | 1.810 | QRP CW Calling Frequency | | |
| | 1.800-1.810 | Digital Modes | | |
| | | 1.800 | | |

80/75 METERS — 3.5-4.0 MHz

| T | G | A | E | 4.000 | | | | | |
|--------------|-----------------------------------|--------------|---|--------------|---------------------------|---|---|--------|--------------|
| █ | █ | █ | █ | 3.990 | W1AW Voice | | | | |
| | | | | 3.985 | QRP SSB Calling Frequency | | | | |
| | | | | 3.885 | AM Calling Frequency | | | | |
| | | | | 3.845 | SSTV | | | | |
| | | | | 3.800 | | | | | |
| | | | | 3.775-3.800 | SSB DX Window | | | | |
| | | | | 3.700 | | | | | |
| | | | | 3.600 | | | | | |
| | | | | █ | █ | █ | █ | 3.5975 | W1AW RTTY |
| | | | | | | | | 3.590 | RTTY/Data DX |
| 3.585-3.600 | Automatically-controlled Data | | | | | | | | |
| 3.5815 | W1AW Code | | | | | | | | |
| 3.580 | PSK31 | | | | | | | | |
| 3.570-3.600 | RTTY/Data | | | | | | | | |
| 3.560 | QRP CW Calling Frequency | | | | | | | | |
| 3.555 | QRS (Slow-speed) CW Calling Freq. | | | | | | | | |
| 3.525 | | | | | | | | | |
| 3.500-3.510 | CW DX Window | | | | | | | | |
| | | 3.500 | | | | | | | |

60 METERS — 5 MHz, Channelized

| G | A | E | | |
|---|---|---|--------|-----------------------------|
| █ | █ | █ | 5.4035 | 5.405 MHz center frequency |
| | | | 5.3715 | 5.373 MHz center frequency |
| | | | 5.3570 | 5.3585 MHz center frequency |
| | | | 5.3465 | 5.348 MHz center frequency |
| | | | 5.3305 | 5.332 MHz center frequency |
| | | | | |

100 watts PEP ERP maximum. Occupied bandwidth limited to 2.8kHz. CW, PSK31, FACTOR-III transmissions must be made at center frequency only.

40 METERS — 7.0-7.3 MHz

| T | G | A | E | 7.300 | | | | | |
|--------------|----------------|--------------|---|--------------|---------------------------|---|---|-------------|-------------------------------|
| █ | █ | █ | █ | 7.290 | W1AW Voice | | | | |
| | | | | 7.290 | AM Calling Frequency | | | | |
| | | | | 7.285 | QRP SSB Calling Frequency | | | | |
| | | | | 7.175 | | | | | |
| | | | | 7.171 | SSTV | | | | |
| | | | | 7.125 | | | | | |
| | | | | █ | █ | █ | █ | 7.100-7.105 | Automatically-controlled Data |
| | | | | | | | | 7.095 | W1AW RTTY |
| | | | | | | | | 7.080-7.125 | RTTY/Data |
| | | | | | | | | 7.070 | PSK31 |
| 7.0475 | W1AW Code | | | | | | | | |
| 7.040 | RTTY/Data DX | | | | | | | | |
| 7.035 | PSK31 | | | | | | | | |
| 7.030 | QRP CW Calling | | | | | | | | |
| 7.025 | | | | | | | | | |
| 7.000-7.025 | CW DX Window | | | | | | | | |
| | | 7.000 | | | | | | | |

30 METERS — 10.1-10.15 MHz

| G | A | E | 10.150 | |
|---|---|---|---------------|-------------------------------|
| █ | █ | █ | 10.142 | PSK31 |
| | | | 10.140-10.150 | Automatically-controlled Data |
| | | | 10.130-10.140 | RTTY/Data |
| | | | 10.106 | QRP CW Calling Frequency |
| | | | 10.100 | |

200 watts PEP maximum.

20 METERS — 14.0-14.35 MHz

| G | A | E | 14.350 | | | | | | |
|----------------|-----------------------------------|---------------|--------|---------------|---------------------------|---|---|----------------|-------------------------------|
| █ | █ | █ | █ | 14.290 | W1AW Voice | | | | |
| | | | | 14.286 | AM Calling Frequency | | | | |
| | | | | 14.285 | QRP SSB Calling Frequency | | | | |
| | | | | 14.230 | SSTV | | | | |
| | | | | 14.225 | | | | | |
| | | | | 14.190-14.200 | SSB DX Window | | | | |
| | | | | 14.175 | | | | | |
| | | | | 14.150 | | | | | |
| | | | | █ | █ | █ | █ | 14.1005-14.112 | Automatically-controlled Data |
| | | | | | | | | 14.100 | Beacons |
| 14.095-14.0995 | Automatically-controlled Data | | | | | | | | |
| 14.095 | W1AW RTTY | | | | | | | | |
| 14.070 | PSK31 | | | | | | | | |
| 14.070-14.095 | RTTY/Data | | | | | | | | |
| 14.060 | QRP CW Calling Frequency | | | | | | | | |
| 14.055 | QRS (Slow-speed) CW Calling Freq. | | | | | | | | |
| 14.0475 | W1AW Code | | | | | | | | |
| 14.025 | | | | | | | | | |
| 14.000-14.025 | CW DX Window | | | | | | | | |
| | | 14.000 | | | | | | | |

17 METERS — 18.068-18.168 MHz

| G | A | E | 18.168 | | |
|---|---|---|--------|---------------|-------------------------------|
| █ | █ | █ | █ | 18.160 | W1AW Voice |
| | | | | 18.130 | QRP SSB Calling Frequency |
| | | | | 18.110 | |
| | | | | 18.105-18.110 | Automatically-controlled Data |
| | | | | 18.1025 | W1AW RTTY |
| | | | | 18.100-18.105 | RTTY/Data |
| | | | | 18.100 | PSK31 |
| | | | | 18.0975 | W1AW Code |
| | | | | 18.068 | |
| | | | | | |

15 METERS — 21.0-21.45 MHz

| T | G | A | E | 21.450 | | | | | |
|---------------|-----------------------------------|---|---|---------------|---------------------------|---|---|---------------|-------------------------------|
| █ | █ | █ | █ | 21.390 | W1AW Voice | | | | |
| | | | | 21.385 | QRP SSB Calling Frequency | | | | |
| | | | | 21.340 | SSTV | | | | |
| | | | | 21.275 | | | | | |
| | | | | 21.225 | | | | | |
| | | | | 21.200 | | | | | |
| | | | | █ | █ | █ | █ | 21.150 | Beacons |
| | | | | | | | | 21.095 | W1AW RTTY |
| | | | | | | | | 21.090-21.100 | Automatically-controlled Data |
| | | | | | | | | 21.070 | PSK31 |
| 21.070-21.100 | RTTY/Data | | | | | | | | |
| 21.0675 | W1AW Code | | | | | | | | |
| 21.060 | QRP CW Calling Frequency | | | | | | | | |
| 21.055 | QRS (Slow-speed) CW Calling Freq. | | | | | | | | |
| 21.025 | | | | | | | | | |
| 21.000 | | | | | | | | | |

12 METERS — 24.89-24.99 MHz

| G | A | E | 24.990 | | |
|---|---|---|--------|---------------|-------------------------------|
| █ | █ | █ | █ | 24.950 | QRP SSB Calling Frequency |
| | | | | 24.930 | |
| | | | | 24.925-24.930 | Beacons |
| | | | | 24.920 | Automatically-controlled Data |
| | | | | 24.920-24.925 | PSK31 |
| | | | | 24.906 | RTTY/Data |
| | | | | 24.890 | QRP CW Calling Frequency |

10 METERS — 28.0-29.7 MHz

| T | G | A | E | 29.700 | |
|---|---|---|---|---------------|-----------------------------------|
| █ | █ | █ | █ | 29.610-29.700 | Repeater Outputs |
| | | | | 29.600 | FM Simplex |
| | | | | 29.520-29.590 | Repeater Inputs |
| | | | | 29.300-29.510 | Satellite Downlinks |
| | | | | 29.000-29.200 | AM |
| | | | | 28.680 | SSTV |
| | | | | 28.590 | W1AW Voice |
| | | | | 28.500 | |
| | | | | 28.385 | QRP SSB Calling Frequency |
| | | | | 28.300 | |
| █ | █ | █ | █ | 28.190-28.225 | Beacons |
| | | | | 28.120 | PSK31 |
| | | | | 28.120-28.189 | Automatically-controlled Data |
| | | | | 28.095 | W1AW RTTY |
| | | | | 28.070-28.120 | RTTY/Data |
| | | | | 28.0675 | W1AW Code |
| | | | | 28.060 | QRP CW Calling Frequency |
| | | | | 28.055 | QRS (Slow-speed) CW Calling Freq. |
| | | | | 28.000 | |
| | | | | | |

| | |
|---|---------------------------|
| █ CW, RTTY, Data, Phone, Image | T – Technician and Novice |
| █ CW, Phone, Image | G – General |
| █ CW, SSB Phone (200W PEP Max) | A – Advanced |
| █ CW, RTTY, Data | E – Amateur Extra |
| █ CW, RTTY, Data (200W PEP Max.) | |
| █ CW Only (200W PEP Max.) | |
| █ USB Phone, CW, PSK31, FACTOR-III Only (100W PEP Max.) | |